



Cisco IP Phone 6800 Series Multiplatform Phones User Guide

First Published: 2017-11-16

Last Modified: 2017-12-20

Americas Headquarters

Cisco Systems, Inc.
170 West Tasman Drive
San Jose, CA 95134-1706
USA
<http://www.cisco.com>
Tel: 408 526-4000
800 553-NETS (6387)
Fax: 408 527-0883

THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS IN THIS MANUAL ARE SUBJECT TO CHANGE WITHOUT NOTICE. ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS MANUAL ARE BELIEVED TO BE ACCURATE BUT ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED. USERS MUST TAKE FULL RESPONSIBILITY FOR THEIR APPLICATION OF ANY PRODUCTS.

THE SOFTWARE LICENSE AND LIMITED WARRANTY FOR THE ACCOMPANYING PRODUCT ARE SET FORTH IN THE INFORMATION PACKET THAT SHIPPED WITH THE PRODUCT AND ARE INCORPORATED HEREIN BY THIS REFERENCE. IF YOU ARE UNABLE TO LOCATE THE SOFTWARE LICENSE OR LIMITED WARRANTY, CONTACT YOUR CISCO REPRESENTATIVE FOR A COPY.

The following information is for FCC compliance of Class A devices: This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio-frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference, in which case users will be required to correct the interference at their own expense.

The following information is for FCC compliance of Class B devices: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If the equipment causes interference to radio or television reception, which can be determined by turning the equipment off and on, users are encouraged to try to correct the interference by using one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Modifications to this product not authorized by Cisco could void the FCC approval and negate your authority to operate the product

The Cisco implementation of TCP header compression is an adaptation of a program developed by the University of California, Berkeley (UCB) as part of UCB's public domain version of the UNIX operating system. All rights reserved. Copyright © 1981, Regents of the University of California.

NOTWITHSTANDING ANY OTHER WARRANTY HEREIN, ALL DOCUMENT FILES AND SOFTWARE OF THESE SUPPLIERS ARE PROVIDED "AS IS" WITH ALL FAULTS. CISCO AND THE ABOVE-NAMED SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING, WITHOUT LIMITATION, THOSE OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NONINFRINGEMENT OR ARISING FROM A COURSE OF DEALING, USAGE, OR TRADE PRACTICE.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: <http://www.cisco.com/go/trademarks>. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1110R)

© 2017 Cisco Systems, Inc. All rights reserved.



CONTENTS

CHAPTER 1

Your Phone 1

- The Cisco IP Phone 6800 Series Multiplatform Phones 2
- New and Changed Features 3
 - New and Changed for Firmware Release 11.1(1) 3
- Phone Setup 3
 - Adjust the Handset Rest 3
 - Connect to the Network 4
 - Set a Password on Initial Phone Boot Up 4
- Sign into Your Extension from Another Phone 5
 - Sign out of Your Extension from Another Phone 5
- Sign In to a Phone as a Guest 5
 - Sign Out of a Phone as a Guest 6
- Set the Profile Rule on the Phone 6
- Monitor a Coworker's Line 6
- Phone Web Page 7
 - Speed-Dial Numbers 8
- Buttons and Hardware 9
 - Navigation 10
 - Softkey, Line, and Feature Buttons 11
 - Phone Screen Features 12
 - Clean the Phone Screen 12
 - Differences Between Phone Calls and Lines 13
- Energy Savings 13
- Additional Help and Information 13
 - Accessibility Features 13
 - Hearing-Impaired Accessibility Features 14
 - Vision-Impaired and Blind Accessibility Features 16
 - Mobility-Impaired Accessibility Features 18

| | |
|--|----|
| Third-Party Accessibility Applications | 20 |
| Troubleshooting | 20 |
| Find Information About Your Phone | 20 |
| View the Customization State on the Phone | 21 |
| View the Network Status | 22 |
| View the Phone Status | 23 |
| View the Status Messages on the Phone | 23 |
| View the Line Status | 23 |
| View the Transaction Status | 24 |
| View the Reboot History | 24 |
| Report All Phone Issues | 24 |
| Factory Reset the Phone from Phone Web Page | 25 |
| Factory Reset the Phone with the Web UI Button | 25 |
| Identify Phone Issues with a URL in the Phone Web Page | 25 |
| Lost Phone Connectivity | 26 |
| Cisco One-Year Limited Hardware Warranty Terms | 26 |

CHAPTER 2**Calls 27**

| | |
|---|----|
| Make Calls | 27 |
| Make a Call | 27 |
| Make a Call with the Speakerphone | 28 |
| Make a Call with a Headset | 28 |
| Redial a Number | 28 |
| Speed Dial | 28 |
| Assign a Speed-Dial Code from the Phone Screen | 29 |
| Make a Call with a Speed-Dial Code | 29 |
| Configure a Speed Dial on a Line Key | 29 |
| Remove a Speed Dial from a Line Key | 30 |
| Use the Line in Focus for Speed-Dial Calls | 30 |
| Use the Line in Focus to Check Speed-Dial Calls | 30 |
| Dial an International Number | 31 |
| Secure Calls | 31 |
| Answer Calls | 31 |
| Answer a Call | 31 |
| Answer Call Waiting | 32 |

| | |
|---|----|
| Decline a Call | 32 |
| Turn On Do Not Disturb | 32 |
| Turn On or Turn Off DND Using a Star Code | 33 |
| Answer a Coworker's Phone (Call Pickup) | 33 |
| Answer a Call Within Your Group (Pickup) | 33 |
| Mute Your Call | 33 |
| Hold Calls | 34 |
| Put a Call on Hold | 34 |
| Answer a Call Left on Hold for Too Long | 34 |
| Swap Between Active and Held Calls | 34 |
| Call Park | 35 |
| Place a Call on Hold with Call Park | 35 |
| Retrieve a Call on Hold with Call Park | 35 |
| Forward Calls | 36 |
| Forward Call in Specific Situations with the Phone Web Page | 36 |
| Transfer Calls | 37 |
| Transfer a Call to Another Person | 37 |
| Consult Before You Complete a Transfer | 38 |
| Conference Calls and Meetings | 38 |
| Add Another Person to a Call | 39 |
| Conference with a Star Code | 39 |
| Page a Group of Phones (Multicast Paging) | 39 |
| Multiple Lines | 40 |
| Answer the Oldest Call First | 40 |
| View All Calls on Your Phone | 40 |
| Shared Lines | 40 |
| Add Yourself to a Call on a Shared Line | 40 |
| Record a Call | 41 |
| Call Center Features | 41 |
| Sign In as a Call Center Agent | 42 |
| Sign Out as a Call Center Agent | 42 |
| Change Your Status as a Call Center Agent | 42 |
| Accept a Call Center Call | 43 |
| Hold an Agent Call | 43 |
| Set a Disposition Code While on a Call Center Call | 43 |

- Trace a Call 44
- Escalate a Call to a Supervisor 44

CHAPTER 3

Contacts 45

- Corporate Directory 45
 - Dial a Contact in the Corporate Directory 45
- Broadsoft Directory 46
 - Search for a Contact in Your Broadsoft Directory (Simple Search) 46
 - Search for a Contact in Your BroadSoft Directory (Advance Search) 46
- LDAP Directory 47
 - Search for a Contact in Your LDAP Directory 47
- Instant Message and Presence Contacts 47
 - Presence 47
 - Make a Call to an IM and Presence Contact 47
 - Change Your Presence State 48
- Personal Address Book 49
 - Add a New Contact to Your Personal Address Book 49
 - Add a New Contact to Your Personal Address Book with Phone Web Page 49
 - Search for a Contact in Your Personal Address Book 49
 - Call a Contact in Your Personal Address Book 50
 - Edit a Contact in Your Personal Address Book 50
 - Remove a Contact from Your Personal Address Book 50

CHAPTER 4

Recent Calls 51

- Recent Calls List 51
- View Your Recent Calls 51
- Return a Recent Call 52
- Clear the Recent Calls List 53
- Create a Contact From a Recents Record 53
- Delete a Call Record 53
- Delete All Call Records 54

CHAPTER 5

Voicemail 55

- Your Voicemail Account 55
 - Set Up Voicemail on Your Phone 55

| | |
|--|--------------------|
| Check for New Voice Messages | 56 |
| Access Voicemail | 56 |
| Access Audio Voicemail | 56 |
| <hr/> | |
| CHAPTER 6 | Settings 57 |
| Settings Overview | 57 |
| User Preferences Menu | 57 |
| Call Preferences | 57 |
| Forward Calls in Specific Situations from Your Phone | 58 |
| Set Up Voicemail | 58 |
| Block Your Caller ID Display | 59 |
| Block an Anonymous Call | 59 |
| Turn On Do Not Disturb For a Specific Line | 59 |
| Control the Call Waiting Tone | 60 |
| Secure a Call | 60 |
| Set Up an Auto Answer Page | 60 |
| Enable the Missed Call Shortcut | 61 |
| Audio Preferences | 61 |
| Set Your Preferred Audio Device | 61 |
| Change the Ringtone | 61 |
| Screen Preferences | 62 |
| Change the Screen Saver | 62 |
| Set the Backlight Timer | 62 |
| Adjust the Phone Screen Contrast | 63 |
| Set the Phone Wallpaper | 63 |
| Attendant Console Preferences | 64 |
| Change the Display Mode | 64 |
| Device Administration Settings | 64 |
| Change the Time Format | 64 |
| Change the Date Format | 65 |
| Set Language | 65 |
| Set up Power Save | 65 |
| Set Password | 66 |
| Phone Web Page Preferences | 66 |
| Assign a Ring Tone to an Extension with the Phone Web Page | 66 |

- Turn on DND on for All Lines from the Phone Web Page 67
- Configure the Screen Saver with the Phone Web Page 67
- Adjust the Backlight Timer from Phone Web Page 68
- Add a Logo as a Phone Background 68
- Restart Your Phone 69

CHAPTER 7

Accessories 71

- Supported Accessories 71
- Headsets 71
 - Standard Headsets 72
 - Connect a Standard Headset 72
 - Enable an E-Hookswitch Headset 72

CHAPTER 8

Product Safety and Security 73

- Safety and Performance Information 73
 - Power Outage 73
 - External Devices 73
 - Ways to Provide Power to Your Phone 74
 - Phone Behavior During Times of Network Congestion 74
- Compliance Statements 74
 - FCC Compliance Statements 74
 - FCC Part 15.21 Statement 74
 - FCC RF Radiation Exposure Statement 74
 - FCC Receivers and Class B Digital Statement 75
 - Compliance Information for Brazil 75
- Cisco Product Security Overview 75
- Important Online Information 76



Your Phone

- [The Cisco IP Phone 6800 Series Multiplatform Phones, page 2](#)
- [New and Changed Features, page 3](#)
- [Phone Setup, page 3](#)
- [Sign into Your Extension from Another Phone, page 5](#)
- [Sign In to a Phone as a Guest, page 5](#)
- [Set the Profile Rule on the Phone, page 6](#)
- [Monitor a Coworker's Line, page 6](#)
- [Phone Web Page, page 7](#)
- [Buttons and Hardware, page 9](#)
- [Energy Savings, page 13](#)
- [Additional Help and Information , page 13](#)

The Cisco IP Phone 6800 Series Multiplatform Phones

The Cisco IP Phone 6800 Series Multiplatform Phones deliver easy-to-use, highly-secure voice communications.

Figure 1: Cisco IP Phone 6800 Series Multiplatform Phones



Table 1: Cisco IP Phone 6800 Series Multiplatform Phones Major Features

| Features | 6841 | 6851 |
|---------------------------------------|---------------------------|---------------------------|
| Screen | Greyscale, with backlight | Greyscale, with backlight |
| Lines | 4 | 4 |
| Fixed feature keys | 9 | 9 |
| Power over Ethernet (PoE) | Not supported | Supported |
| Electronic Hookswitch Headset support | Not supported | Supported |

Your phone must be connected to a network and configured to connect to a call control system. The phones support many functions and features, depending on the call control system. Your phone might not have all functions available, based on the way your administrator has set it up.

When you add features to your phone, some features require a line button. But each line button on your phone can support only one function (a line, a speed dial, or a feature). If your phone's line buttons are already in use, your phone won't display any additional features.

Related Topics

[Find Information About Your Phone, on page 20](#)

New and Changed Features

New and Changed for Firmware Release 11.1(1)


| Feature | New or Changed Sections |
|---------------------------------|--|
| Call Center Support | Call Center Features, on page 41 |
| Call Recording | Record a Call, on page 41 |
| Contrast Adjustment Enhancement | Adjust the Phone Screen Contrast, on page 63 |
| Power Save Support | Set up Power Save, on page 65 |
| Presence | Instant Message and Presence Contacts, on page 47 Change Your Presence State, on page 48 Make a Call to an IM and Presence Contact, on page 47 |

Phone Setup

Typically, your administrator sets up your phone and connects it to the network. If your phone is not set up and connected, contact your administrator for instructions.

Adjust the Handset Rest

If your phone is wall-mounted or if the handset slips out of the cradle too easily, you may need to adjust the handset rest to ensure that the receiver does not slip out of the cradle.



Procedure

-
- Step 1** Remove the handset from the cradle and pull the plastic tab from the handset rest.
 - Step 2** Rotate the tab 180 degrees.
 - Step 3** Hold the tab between two fingers, with the corner notches facing you.
 - Step 4** Line up the tab with the slot in the cradle and press the tab evenly into the slot. An extension protrudes from the top of the rotated tab.
 - Step 5** Return the handset to the handset rest.
-

Connect to the Network

You need to connect the phone to the telephone network.

- Wired connection—The phone is plugged into the network using an Ethernet cable.

Set a Password on Initial Phone Boot Up

The first time your phone boots up, you may be prompted to set a password. If you are not prompted, your administrator has created a password for you.

Procedure

-
- Step 1** Enter your password in the **New password** and **Reenter new password** fields.
 - Step 2** Press **Save**.
-

Sign into Your Extension from Another Phone

If extension mobility is configured, you can sign into a different phone in your network and have it act the same as your phone. After you sign in, the phone adopts your personal directory number.

Before You Begin

Your administrator configures provisioning authority.

Procedure

- Step 1** Press **Sign in**.
 - Step 2** Enter your username and password, then press **Sign in**.
The password field allows two input methods: alphanumeric and numeric. While you type in the password, you see the **Options** softkey on the phone. Use this softkey to change the current password input type. Select **Input all** for alphanumeric input and select **Input num** for numeric entry. Your administrator configures the password input method on the phone web page.
-

Sign out of Your Extension from Another Phone

Procedure

Press **Sign out**.

Sign In to a Phone as a Guest

You can sign in to a different phone in your network as a guest.

Procedure

- Step 1** Press **Sign in**.
 - Step 2** Enter your user ID and password.
The password field allows two types of input method; alphanumeric and numeric. While you type in the password, you see **Options** softkey on the phone. You can use this softkey to change the current password input type. Select **Input all** for alphanumeric input and select **Input num** for numeric entry.
 - Step 3** Press **Save**.
-

Sign Out of a Phone as a Guest

Procedure

Step 1 Press **Guest Out**.

Step 2 Press **Sign Out**.

Set the Profile Rule on the Phone

Procedure

Step 1 Press **Applications** .

Step 2 Select **Device administration > Profile rule**.

Step 3 Press **Resync**.

Monitor a Coworker's Line

With the busy lamp field feature, you can monitor the line status of a coworker or supervisor. This feature is useful if you routinely handle calls for a colleague and need to see their ability to answer a call.





































If this feature is configured on your phone, the following LED colors display on a line key:

- A green LED—Monitored line is available.
- A red LED—Monitored line is busy.
- A red fast blinking LED—A call is ringing to the monitored line.
- An amber LED—A configuration error occurred when this feature was being set up.

On your phone, you see the caller ID for the calls that you receive. For lines that you monitor, you do not see caller ID.

You can use this feature with speed dial or call pickup for even greater flexibility. You may see different icons displayed on your phone based on your combination of features. The following table shows the various busy lamp field icons based on each feature combination.

Table 2: Busy Lamp Field Icons on the Cisco IP Phone 7800 Series

| | Busy Lamp Field | Busy Lamp Field and Speed Dial | Busy Lamp Field and Call Park | Busy Lamp Field and Call Pickup | Busy Lamp Field, Speed Dial, and Call Pickup | Busy Lamp Field, Speed Dial, and Call Park | Busy Lamp Field, Call Pickup, and Call Park | Busy Lamp Field, Speed Dial, Call Pickup, and Call Park |
|-------------|--|--|--|--|--|--|--|--|
| Idle |  |  |  |  |  |  |  |  |
| Alerting |  |  |  |  |  |  |  |  |
| In use |  |  |  |  |  |  |  |  |
| Call parked | - | - |  | - | - |  |  |  |
| Error |  |  |  |  |  |  |  |  |

Phone Web Page

You can customize some phone settings with the phone web page, which you access from your computer. Your administrator gives you the page URL, your user ID, and password.

In the phone web page, you can control features, line settings, and phone services for your phone.

- Phone features include speed dial, do not disturb, and your personal address book.
- Line settings affect a specific phone line (directory number) on your phone. Line settings can include call forwarding, visual and audio message indicators, ring patterns, and other line-specific settings.

The following table describes some specific features that you configure using the phone web page.

| Features | Description |
|--------------|--|
| Call forward | You specify the number that will receive calls when call forward is enabled on the phone. Use the phone web page to set up more complicated call forward functions, for example, when your line is busy. |
| Speed dial | You assign phone numbers to speed-dial numbers so that you can quickly call that person. |
| Ringtone | You assign a ringtone to a specific line. |

| Features | Description |
|----------------------------|---|
| Personal directory contact | You add a contact to your personal directory with phone web page. |

Related Topics

[Speed Dial, on page 28](#)

[Forward Calls, on page 36](#)

Speed-Dial Numbers

When you dial a number on your phone, you enter a series of digits. When you set up a speed-dial number, the speed-dial number must contain all the digits you need to make the call. For example, if you need to dial 9 to get an outside line, you enter the number 9 and then the number you want to dial.

You can also add other dialed digits to the number. Examples of additional digits include a meeting access code, an extension, a voicemail password, an authorization code, and a billing code.

The dial string can contain the following characters:

- 0 to 9
- Pound (#)
- Asterisk (*)
- Comma (,)—This is the pause character, and gives a 2-second delay in the dialing. You can have several commas in a row. For example, two commas (,,) represent a pause of 4 seconds.

The rules for dial strings are:

- Use the comma to separate the parts of the dial string.
- An authorization code must always precede a billing code in the speed-dial string.
- A single comma is required between the authorization code and the billing code in the string.
- A speed-dial label is required for speed dials with authorization codes and additional digits.

Before you configure the speed dial, try to dial the digits manually at least once to ensure that the digit sequence is correct.



Note

Your phone does not save the authorization code, billing code, or extra digits from the speed dial in the call history. If you press **Redial** after you connect to a speed-dial destination, the phone prompts you to enter any required authorization code, billing code, or additional digits manually.

Example

To set up a speed-dial number to call a person at a specific extension, and if you need an authorization code and billing code, consider the following requirements:

- You need to dial 9 for an outside line.
- You want to call 5556543.
- You need to input the authorization code 1234.
- You need to input the billing code 9876.
- You must wait for 4 seconds.
- After the call connects, you must dial the extension 56789#.


In this scenario, the speed-dial number is 95556543,1234,9876,,56789#.













Buttons and Hardware

The following figure shows the Cisco IP Phone 6841.

Figure 2: Cisco IP Phone 6800 Series Buttons and Features



| | | |
|---|---|--|
| 1 | Handset and Handset light strip | Indicates whether you have an incoming call (flashing red) or a new voice message (steady red). |
| 2 | Programmable feature buttons and line buttons |  Access your phone lines, features, and call sessions. For more information, see Softkey, Line, and Feature Buttons , on page 11. |

| | | |
|---|--|---|
| 3 | Softkey buttons |  Access functions and services. For more information, see Softkey, Line, and Feature Buttons, on page 11 . |
| 4 | Navigation cluster | Navigation ring and Select  button. Scroll through menus, highlight items, and select the highlighted item. |
| 5 | Hold/Resume, Conference, and Transfer | Hold/Resume  Place an active call on hold and resume the held call. Conference  Create a conference call. Transfer  Transfer a call. |
| 6 | Speakerphone, Mute, and Headset | Speakerphone  Toggle the speakerphone on or off. When the speakerphone is on, the button is lit. Mute  Toggle the microphone on or off. When the microphone is muted, the button is lit. Headset  Toggle the headset on or off. When the headset is on, the button is lit. |
| 7 | Contacts, Applications, and Messages | Contacts  Access personal and corporate directories. Applications  Access call history, user preferences, phone settings, and phone model information. Messages  Autodial your voice messaging system. |
| 8 | Volume button |  Adjust the handset, headset, and speakerphone volume (off hook) and the ringer volume (on hook). |

Navigation

Use the outer ring of the Navigation cluster to scroll through menus and between lines. Use the inner **Select** button of the Navigation cluster to select items.







If a menu item has an index number, you can enter the index number with the keypad to select the item.

Softkey, Line, and Feature Buttons

You can interact with the features on your phone in several ways:

- Softkeys, located below the screen, give you access to the function displayed on the screen above the softkey. The softkeys change depending on what you are doing at the time. The **More ...** softkey shows you that more functions are available.
- Feature and line buttons, located on either side of the screen, give you access to phone features and phone lines.
 - Feature buttons—Used for features such as **Speed dial** or **Call pickup**, and to view your status on another line.
 - Line buttons—Used to initiate or answer a call or resume a held call. You can also use a line key to open and close the call session window, and to navigate through the call session window. Open the call session window to see the calls on the line.

Feature and line buttons illuminate to indicate status:

-  Green—Line is idle.
-  Red, steady—Line is active or in use.
-  Red, flashing—Line is on hold or there is an inbound call.
-  Amber, steady—Line is unregistered (cannot be used).

Your administrator can set up some functions as softkeys or as feature buttons. You can also access some functions with softkeys or the associated hard button.

Phone Screen Features

The phone screen shows information about your phone such as directory number, active call and line status, softkeys, speed dials, placed calls, and phone menu listings. The screen is made up of three sections: the header row, the middle section, and the footer row.

Figure 3: Cisco IP Phone 6800 Screen





Figure 4: Cisco IP Phone 7800 Screen



| | |
|---|---|
| 1 | At the top of the screen is the header row. The header row displays the phone number, current date and time, as well a number of icons. The icons display when features are active. |
| 2 | The middle of the phone screen displays the information associated with the line and feature buttons on the phone. When you select a line which has more than two registered lines, a black box highlight around the selected line is displayed. There will be no highlight for an active call. Active and incoming call screen supports more than 21 characters. The Cisco IP Phone can display 15 digits on the phone screen when line is inactive. |
| 3 | The bottom row of the screen contains the softkey labels. Each label indicates the action for the softkey button below the screen. |

Clean the Phone Screen

Procedure

If your phone screen gets dirty, wipe it with a soft, dry cloth.

Caution Do not use any liquids or powders on the phone because they can contaminate the phone components and cause failures.

Differences Between Phone Calls and Lines

We use the terms *lines* and *calls* in very specific ways to explain how to use your phone.

- **Lines**—Each line corresponds to a directory number or intercom number that others can use to call you. You have as many lines as you have directory numbers and phone line icons.
- **Calls**—Each line can support multiple calls. By default, your phone supports two connected calls per line, but your administrator can adjust this number according to your needs.

Only one call can be active at any time; other calls are automatically placed on hold.

Here is an example: If you have two lines and each line supports four calls, then you could have up to eight connected calls at one time. Only one of those calls is active and the other seven are held calls.

Energy Savings

Your administrator can reduce the amount of power that the phone screen uses when you're not using your phone. Level of energy-saving that your administrator can set up:

- **Power Save**—The backlight or screen turns off when the phone has been inactive for a period of time.

Additional Help and Information

If you have questions about the functions available on your phone, contact your administrator.

The Cisco website (<https://www.cisco.com>) contains more information about the phones and call control systems.

- For quick start guides and end-user guides in English, follow this link:

<https://www.cisco.com/c/en/us/support/collaboration-endpoints/ip-phone-6800-series-multiplatform-firmware/products-user-guide-list.html>

- For guides in languages other than English, follow this link:

<https://www.cisco.com/c/en/us/support/collaboration-endpoints/ip-phone-6800-series-multiplatform-firmware/tsd-products-support-translated-end-user-guides-list.html>

- For licensing information, follow this link:

<https://www.cisco.com/c/en/us/support/collaboration-endpoints/ip-phone-6800-series-multiplatform-firmware/products-licensing-information-listing.html>

Accessibility Features

The Cisco IP Phone 6800 Series Multiplatform Phones provide accessibility features for the blind, and the visually, hearing, and mobility impaired. Because many of these features are standard, they can be used by users with disabilities without requiring any special configuration.

In this document, the term *phone support pages* refers to the web pages that users can access to set up certain features.

Cisco is committed to designing and delivering accessible products and technologies to meet the needs of your organization. You can find more information about Cisco and its commitment to accessibility at this URL: <http://www.cisco.com/go/accessibility>

Hearing-Impaired Accessibility Features

Your phone comes with standard accessibility features that require little or no setup.


To check which phone model you have, press **Applications**  and select **Status > Product information**. The **Product name** field shows your phone model.

Figure 5: Hearing-Impaired Accessibility Features—Cisco IP Phone 6841 Multiplatform Phones Shown



Table 3: Hearing-Impaired Accessibility Features

| Item | Accessibility Feature | Description |
|------|--|---|
| 1 | Visual message-waiting indicator (handset) | This lighted strip is visible from all angles. Your phone also provides an audible message-waiting indicator. |

| Item | Accessibility Feature | Description |
|------|--|---|
| 2 | Visual notification of the phone state | <ul style="list-style-type: none"> • Toggle the Mute and Speakerphone buttons on and off to indicate the phone state. • Use the Mute button to toggle the microphone on or off. When the microphone is muted, the button is lit. • Use the Speakerphone button to toggle the speakerphone on or off. When the speakerphone is on, the button is lit. |
| 3 | Inline-amplifier support (handset) | Cisco IP Phone handsets support third-party inline amplifiers. You attach an amplifier to the handset and cord and it sits between the handset and the IP phone. |
| 4 | Adjustable ringtone, pitch, and volume | <ul style="list-style-type: none"> • Select Applications > User preferences. • Adjust the volume level for the phone ring. While the handset is in the cradle and the headset and speakerphone buttons are off, press Volume to raise or lower the volume. <p>Your administrator can also change your settings.</p> |
| 5 | Hearing aid compatible (HAC) handset | <p>Supports these accessibility features:</p> <ul style="list-style-type: none"> • Hearing-aid compatible. • Magnetic coupling of the hearing aid. • Federal Communications Commission (FCC) loudness requirements for the Americans with Disabilities Act (ADA). • Section 508 loudness requirements, which are met by using industry-standard inline handset amplifiers. |
| 6 | Acoustic coupled TTY and TDD support (handset) | <p>Cisco IP Phones support these TTY and TDD features:</p> <ul style="list-style-type: none"> • Acoustic or direct connect TTYs from industry-leading manufacturers. • Real-time text transmission over phone lines. • Hearing and voice carry over phones (HCO/VCO). • VoIP network operating at G.711. <p>For information about setting up TTY, contact your administrator.</p> |

Vision-Impaired and Blind Accessibility Features

Your phone comes with standard accessibility features that require little or no setup.





To check which phone model you have, press **Applications**  and select **Status > Product information**. The **Product name** field shows your phone model.

Figure 6: Vision-Impaired and Blind Accessibility Features—Cisco IP Phone 6841 Multiplatform Phones Shown



Table 4: Vision-Impaired and Blind Accessibility Features

| Item | Accessibility Feature | Description |
|------|--|---|
| 1 | High-contrast visual and audible alert of an incoming call | Alerts you to an incoming call. The handset light strip flashes during incoming calls and stays lit when a voicemail message is received. |

| Item | Accessibility Feature | Description |
|------|---|---|
| 2 | <p>Line and feature buttons on the Cisco IP Phone</p> <p>The line and feature buttons are on the left and right sides of the screen.</p> | <p>Use line buttons to start, answer, or switch to a call on a particular line.</p> <p>Features, such as speed dial, line status, privacy, do not disturb (DND), and service URLs, can be assigned to feature buttons.</p> <p>Your administrator sets up programmable feature buttons on your phone.</p> <p>Colors indicate your phone's status:</p> <ul style="list-style-type: none"> •  Green—Line is idle. •  Red, steady—Line is active or in use. •  Red, flashing—Line is on hold or there is an inbound call. •  Amber, steady—Line is unregistered (cannot be used). |
| 3 | <p>Back-lit grayscale LCD screen with adjustable contrast on the Cisco IP Phone</p> | <p>Allows you to adjust your phone screen's contrast.</p> |
| 4 | <p>Softkeys</p> <ul style="list-style-type: none"> • These are large buttons just below the LCD. | <p>Provide access to special functions. The functions are displayed on the LCD.</p> |
| 5 | <p>Navigation Cluster (includes the Navigation ring and the Select button)</p> <ul style="list-style-type: none"> • The Navigation cluster is located in the center of the phone. | <p>Use the Navigation ring to move up and down in the phone LCD. The Select button is in the center of the Navigation cluster.</p> |
| 6 | <p>Hold button, Transfer button, and Conference button</p> <ul style="list-style-type: none"> • These three large buttons are located to the right of Navigation cluster. • In this group of buttons, the Hold button is the single button in the top row. Below the Hold button, the Transfer button is on the left, and the Conference button is on the right. | <p>Allow you to use these functions on your phone.</p> |

| Item | Accessibility Feature | Description |
|------|--|---|
| 7 | <p>Messages button, Applications button, and Contacts button</p> <ul style="list-style-type: none"> • These three large buttons are located to the left of the Navigation cluster. • In this group of buttons, the Messages button is the single button in the top row. Below the Messages button, the Applications button is on the left, and the Contacts button is on the right. | Allow you to easily access your messages, applications, and contacts. |
| 8 | <p>Volume key</p> <ul style="list-style-type: none"> • This key is located to the left of the keypad. | <p>Allows you to increase or decrease the ring volume or the sound through the handset, headset, or speakerphone.</p> <p>Press up on the rocker key to increase the volume. Press down on the rocker key to decrease the volume.</p> |
| 9 | Standard 12-key layout | Allows you to use existing or familiar key positions. Key 5 has a nib. |
| 10 | <ul style="list-style-type: none"> • Headset, Speakerphone, and Mute buttons located to the right of the keypad. • The Speakerphone button is on the top, the Headset button is in the middle, and the Mute button is on the bottom. | <p>Provide audible notification of the phone state:</p> <ul style="list-style-type: none"> • Toggle the Headset, Mute, and Speakerphone buttons on and off to indicate the phone state. • Use the Headset button to toggle the headset on or off. When the headset is on, the button is lit. • Use the Mute button to toggle the microphone on or off. When the microphone is muted, the button is lit. When you turn on Mute, your phone beeps once; when you turn off Mute, your phone beeps twice. • Use the Speakerphone button to toggle the speakerphone on or off. When the speakerphone is on, the button is lit. |

Mobility-Impaired Accessibility Features





Your phone comes with standard accessibility features that require little or no setup.

To check which phone model you have, press **Applications**  and select **Status > Product information**. The **Product name** field shows your phone model.

Figure 7: Mobility-Impaired Accessibility Features—Cisco IP Phone 6841 Multiplatform Phones Shown



Table 5: Mobility-Impaired Accessibility Features

| Item | Accessibility Feature | Description |
|------|-----------------------|---|
| 1 | Lighted buttons | <p>Allow you to access the following features:</p> <ul style="list-style-type: none"> • Phone lines and intercom lines (line buttons) • Speed-dial numbers (speed-dial buttons, including the speed-dial line status feature) • Web-based services, such as a personal address book • Phone features, such as privacy <p>Indicate your phone's status:</p> <ul style="list-style-type: none"> •  Green—Line is idle. •  Red, steady—Line is active or in use. •  Red, flashing—Line is on hold or there is an inbound call. •  Amber, steady—Line is unregistered (cannot be used). |

| Item | Accessibility Feature | Description |
|------|---|---|
| 2 | Large buttons to access Applications, Messages, Contacts, Hold, Transfer, and Conference | Allow you to easily access your phone applications, voice messages, corporate and personal directories, and calling features. |
| 3 | Built-in speakerphone | Indicates whether the speakerphone is on or off. When the speakerphone is on, the button is lit. |
| 4 | Tactile-discernible buttons and functions, including a nib on Key 5 | Allow you to easily locate your phone's keys. For example, Key 5 has a nib, which you can use to locate other key positions. |

Third-Party Accessibility Applications

Cisco works closely with partners to provide solutions that complement the Accessibility and usability of Cisco Products and Solutions. There are third-party applications such as real-time Captioning on Cisco IP phones, Text Telephones for the Deaf (TDD/TTY), Real Time Text (RTT), hearing/voice carry over (HCO/VCO), audible Caller ID, Inline amplifiers for handsets for louder call sound, "busy lights", audio/visual emergency notifications through Cisco IP phones (supporting users with disabilities), etc.

Here's a link to a presentation about all the accessibility features of Cisco Unified Communications products, and some third party assistive technology which works with it:

http://www.cisco.com/c/dam/en_us/about/responsibility/accessibility/products/Accessibility_Innovation_Cisco_Unified_Communications.pdf

For more information about third-party applications, contact your administrator.

Troubleshooting

You may experience issues related to the following scenarios:


- Your phone cannot communicate with the call control system.
- The call control system has communication or internal problems.
- Your phone has internal problems.

If you experience problems, your administrator can help troubleshoot the root cause of the problem.

Find Information About Your Phone

Your administrator may ask for information about your phone. This information uniquely identifies the phone for troubleshooting purposes.

Procedure

- Step 1** Press **Applications** .
- Step 2** Select **Status > Product Information**.
You can view the following information:
- Product name**— Model number of the Cisco IP Phone.
- Serial number**— Serial number of the Cisco IP Phone.
- MAC address**—Hardware address of the Cisco IP Phone.
- Software version**—Version number of the Cisco IP Phone firmware.
- Hardware version**—Version number of the Cisco IP Phone hardware.
- Certificate**—Status of the client certificate, which authenticates the Cisco IP Phone for use in the ITSP network. This field indicates if the client certificate is properly installed in the phone.
- Customization**—For an RC unit, this field indicates whether the unit has been customized or not. Pending indicates a new RC unit that is ready for provisioning. If the unit has already retrieved its customized profile, this field displays the Customization state as Acquired.
- Step 3** Press **Back** to return to the Applications screen.
-

View the Customization State on the Phone

After the RC download from the EDOS server completes, you can view the customization state of a phone on the LCD UI.

Here are the descriptions of the remote customization states:


- **Open**—The phone has booted for the first time and is not configured.
- **Aborted**—Remote Customization is aborted due to other Provisioning like DHCP options.
- **Pending**—The profile has been downloaded from the EDOS server.
- **Custom-Pending**—The phone has downloaded a redirect URL from the EDOS server.
- **Acquired**—In the profile downloaded from the EDOS server, there is a redirect URL for provision configuration. If the redirect URL download from the provisioning server is successful, this state is displayed.
- **Unavailable**—Remote customization has stopped because the EDOS server responded with an empty provisioning file and the HTTP response was 200 OK.

Procedure

- Step 1** Press **Applications** .
- Step 2** Select **Status > Product information > Customization**.
- Step 3** Press **Back**.
-


View the Network Status

Procedure

- Step 1** Press **Applications** .
- Step 2** Select **Status > Network Status**.
You can view the following information:
- **Network type**—Indicates the type of Local Area Network (LAN) connection that the phone uses.
 - **Network status**—Indicates if the phone is connected to a network.
 - **IPv4**—IP address of the phone. You can see information on IP address, VLAN ID, Addressing type, IP status, Subnet mask, Default router, Domain Name Server (DNS) 1, DNS 2 of the phone.
 - **IPv6**—IP address of the phone. You can see information on IP address, VLAN ID, Addressing type, IP status, Subnet mask, Default router, Domain Name Server (DNS) 1, DNS 2 of the phone.
 - **MAC address**—Unique Media Access Control (MAC) address of the phone.
 - **Host name**—Displays the current host name assigned to the phone.
 - **Domain**—Displays the network domain name of the phone. Default: cisco.com
 - **Switch port link**—Status of the switch port.
 - **Switch port config**—Indicates speed and duplex of the network port.
 - **PC port config**—Indicates speed and duplex of the PC port.
 - **PC port link**—Indicates speed and duplex of the PC port.
-


View the Phone Status

Procedure

- Step 1** Press **Applications** .
- Step 2** Select **Status > Phone Status > Phone Status**.
You can view the following information:
- **Elapsed time**—Total time elapsed since the last reboot of the system
 - **Tx (Packets)**—Transmitted packets from the phone.
 - **Rx (Packets)**—Received packets from the phone.
-


View the Status Messages on the Phone

Procedure

- Step 1** Press **Applications** .
- Step 2** Select **Status > Status messages**.
You can view a log of the various phone statuses since provisioning was last done.
Note Status messages reflect UTC time and are not affected by the timezone settings on the phone.
- Step 3** Press **Back**.
-


View the Line Status

Procedure

- Step 1** Press **Applications** .
- Step 2** Select **Status > Phone status > Line status**.
You can view the status of each line on the phone.
-


View the Transaction Status

Procedure

- Step 1** Press **Applications** .
- Step 2** Select **Network configuration > Ethernet configuration > 802.1X authentication > Transaction status**. You can view the following information:
- **Transaction status**
 - **Protocol**
-

View the Reboot History


Procedure

- Step 1** Press **Applications** .
- Step 2** Select **Status > Reboot history**. You can view the details of the date and time whenever the phone has rebooted, no matter why the phone rebooted.
-

Report All Phone Issues

You can use the Problem Reporting Tool (PRT) to collect and send phone logs, and to report problems to your administrator.

Procedure

- Step 1** Press **Applications** .
- Step 2** Select **Status > Report problem**.
- Step 3** Enter the date that you experienced the problem in the **Date of problem** field. The current date appears in this field by default.
- Step 4** Enter the time that you experienced the problem in the **Time of problem** field. The current time appears in this field by default.
- Step 5** Select **Problem description**.
- Step 6** Select a description from the displayed list.
- Step 7** Press **Submit**.
-

Factory Reset the Phone from Phone Web Page

You can restore your phone to its original manufacturer settings from the phone web page. After you reset the phone, you can reconfigure it.

Procedure

Enter the URL in a supported web browser and click **Confirm Factory Reset**

Factory Reset the Phone with the Web UI Button

You can factory reset the phone from the phone web page. The reset only happens if the phone is idle. If the phone is not idle, the phone web page shows a message that the phone is busy and that you need to try again.

Procedure

-
- Step 1** On the phone web page, select **Admin Login > advanced > Info > Debug Info**.
 - Step 2** In the **Factory Reset** section, click **Factory Reset**.
 - Step 3** Click **Confirm factory reset**.
-

Identify Phone Issues with a URL in the Phone Web Page

When the phone doesn't work or doesn't register, a network error or any misconfiguration might be the cause. To identify the cause, add a specific IP address or a domain name to the phone admin page. Then, try to access so that the phone can ping the destination and display the cause.

Procedure

In a supported web browser, enter a URL that consists of your phone IP address and the destination IP that you want to ping.

Enter a URL in the format:

```
http://<Phone IP>/admin/ping?<ping destination>
```

where:

Phone IP = actual IP address of your phone.

/admin = path to access admin page of your phone.

ping destination = any IP address or domain name that you want to ping. Only alphanumeric characters, '-', and '_' are allowed as the ping destination. Otherwise the phone shows an error on the web page. If the <ping destination> includes spaces, only the first part of the address is used as the pinging destination. For example, "http://<Phone IP>/admin/ping?192.168.1.1 cisco.com" will actually ping 192.168.1.1.

Lost Phone Connectivity

Sometimes your phone can lose its connection to the call control system. When this connection is lost, your phone displays a message.

If you are on an active call when the connection is lost, the call continues. However, you do not have access to all normal phone functions because some functions require information from the call control system. Your softkeys might not work as you expect.

When the phone reconnects to the call control system, you'll be able to use your phone normally again.

Cisco One-Year Limited Hardware Warranty Terms

Special terms apply to your hardware warranty and services that you can use during the warranty period.

Your formal Warranty Statement, including the warranties and license agreements applicable to Cisco software, is available on Cisco.com at this URL: <https://www.cisco.com/go/hwwarranty>.



Calls

- [Make Calls, page 27](#)
- [Answer Calls, page 31](#)
- [Mute Your Call, page 33](#)
- [Hold Calls, page 34](#)
- [Forward Calls, page 36](#)
- [Forward Call in Specific Situations with the Phone Web Page, page 36](#)
- [Transfer Calls, page 37](#)
- [Conference Calls and Meetings, page 38](#)
- [Page a Group of Phones \(Multicast Paging\), page 39](#)
- [Multiple Lines, page 40](#)
- [Record a Call, page 41](#)
- [Call Center Features, page 41](#)

Make Calls

Your phone works just like a regular phone. But we make it easier for you to make calls.

Related Topics

[Make a Call to an IM and Presence Contact, on page 47](#)

Make a Call

Use your phone just like any other phone to make a call.

Procedure

Enter a number and pick up the handset.

Make a Call with the Speakerphone

Use your speakerphone for hands-free calling. Keep in mind that your coworkers might be able to hear your call too.

Procedure

Step 1 Enter a number using the keypad.

Step 2 Press **Speakerphone** .

Make a Call with a Headset

Use your headset for hands-free calling that won't disturb your coworker and gives you some privacy.

Procedure

Step 1 Plug in a headset.

Step 2 Enter a number using the keypad.

Step 3 Press **Headset** .

Redial a Number

Use your phone just like any other phone to make a call.

Procedure

Step 1 (Optional) Select a line.

Step 2 Press **Redial**.

Speed Dial

Speed Dial allows you to press a button, enter a preset code, or select a phone screen item to place a call. You can configure the speed dial from the phone screen and also from the phone web page.

You can edit, delete, and validate a speed-dial code.

Related Topics


[Phone Web Page](#), on page 7

[Speed-Dial Numbers](#), on page 8

Assign a Speed-Dial Code from the Phone Screen

You can configure a speed-dial index from your phone screen. You can also assign a speed-dial code from the phone web page.

Procedure

-
- Step 1** Press **Applications** .
- Step 2** Select **Speed dial**.
- Step 3** Scroll to an unassigned speed-dial index.
- Step 4** Press **Edit** and do one of the following:
- Enter the name and number.
 - Select **Option** > **Select from contact** to select a contact from the address book.
- Step 5** Select **Save**
-

Make a Call with a Speed-Dial Code

Before You Begin

Set up speed-dial codes on the phone web page or from your phone's **Applications** menu.

Procedure

Enter the speed-dial code and press **Call**.

Configure a Speed Dial on a Line Key

You can press any idle line key on your phone and set up speed dial on it. The speed-dial icon, the name, and the extension number are displayed on your phone screen next to the line key. You can also verify this change by checking the **Extended Function** field on the web page. After you configure the speed dial on a line key, you can press the line key to modify the speed-dial information and assign a new phone number and name.

Before You Begin

Go to the web page and disable the line key that will become the speed dial key.

Procedure

- Step 1** Press any idle line key on your phone for at least two seconds.
 - Step 2** In the **Speed-Dial** window, add the speed-dial name and phone number to call when you press this line key.
 - Step 3** Click **Save**.
-

Remove a Speed Dial from a Line Key

You can press a line key on your phone and delete speed dial assigned to it. The speed dial on the line key is removed. Check the phone web page to confirm that the speed dial is removed.

Procedure

- Step 1** Press a line key that has a speed dial configured for at least two seconds.
 - Step 2** Press **Option > Delete** in the **Speed-Dial** window on the phone screen.
-

Use the Line in Focus for Speed-Dial Calls

You can configure a line key to perform a speed dial either with a Voice Profile ID (VID) or without a VID. When both are configured, VID has a higher priority. The call is routed to that line.

If a line key is configured without VID, you can configure a speed-dial key to use the line in focus.

Procedure

- Step 1** Configure a speed-dial key without using VID.
- Step 2** Change the focus to the line that you prefer.
- Step 3** Press the speed-dial key to make a call.
The call is made with the line in focus.

If the existing number of calls on the line in focus is equal to the value set in the **Call Appearances Per Line** field in the phone web page, the speed-dial call is made from the next available line.

Use the Line in Focus to Check Speed-Dial Calls

If a line key is configured without VID, you can perform a check to confirm whether the call is made with the line in focus.

Procedure

- Step 1** Configure a speed-dial key without using VID.
 - Step 2** Change the focus to the line that you prefer.
 - Step 3** Press the speed-dial key to make a call.
The call is made with the line in focus.
-

Dial an International Number

You can dial international calls when you prefix the phone number with a plus (+) sign.

Procedure

- Step 1** Press and hold **star (*)** for at least 1 second.
The plus (+) sign is displayed as the first digit in the phone number.
 - Step 2** Dial the number.
Ten seconds after the last key press, the phone dials the number.
-

Secure Calls

Your administrator can take steps to protect your calls from tampering by people outside your company. When a lock icon is displayed on your phone during a call, your phone call is secure. Depending upon how your phone is configured, you may have to sign on before you make a call or before a security tone plays over your handset.

Answer Calls

Your Cisco IP Phone works just like a regular phone. But we make it easier for you to answer calls.

Answer a Call

Use your phone just like any other phone to make a call.

Procedure

Press the flashing red line button.

Answer Call Waiting

When you're on an active call, you know that a call is waiting when you hear a single beep and the line button flashes red.

Procedure

Step 1 (Optional) If you have more than one call waiting, select an incoming call.

Step 2 Press the line button.

Decline a Call

You can send an active or ringing call to your voicemail system or to a preset phone number.

Procedure

Decline a call by performing one of the following actions:

- Press **Decline**.
- If you have multiple incoming calls, highlight the incoming call and press **Decline**.

Turn On Do Not Disturb

Use Do Not Disturb (DND) to silence your phone and ignore incoming call notifications when you need to avoid distractions.

When you enable DND, your incoming calls forward to another number, such as your voicemail, if it is set up.

When DND is turned on, **Do not disturb** is displayed in the top bar of the phone screen.

When you enable DND, by default, it affects all lines on your phone. You can also enable DND on a specific line from the **Preferences** menu. However, you will always receive intercom and emergency calls, even when DND is turned on.

Procedure

Step 1 Press **DND** to turn on DND.

Step 2 Press **Clr DND** again to turn off DND.

Related Topics

[Phone Web Page](#), on page 7

[Turn On Do Not Disturb For a Specific Line](#), on page 59

Turn On or Turn Off DND Using a Star Code

You can turn on or turn off the do not disturb feature by dialing the respective star codes that are configured for your phone. The administrator enters the star codes in the **DND Act Code** and **DND Deact Code** fields respectively on the phone web page.

Procedure

-
- Step 1** To turn on DND, dial the star code provided by your administrator.
 - Step 2** To turn off DND, dial the star code provided by your administrator.
-

Answer a Coworker's Phone (Call Pickup)

If you share call handling tasks with your coworkers, you can answer a call that is ringing on a coworker's phone. First, your administrator has to assign you to at least one call pickup group.

Answer a Call Within Your Group (Pickup)

You can answer a call that rings on another phone within your call pickup group. If multiple calls are available for pickup, you'll answer the call that has been ringing for the longest time.

Procedure

-
- Step 1** (Optional) Press the line button.
 - Step 2** Press **PickUp** to transfer an incoming call within your pickup group to your phone.
-

Mute Your Call

While you are on a call, you can mute the audio so that you can hear the other person, but they cannot hear you.

Procedure

Step 1 Press **Mute** .

Step 2 Press **Mute** again to turn mute off.

Hold Calls

Put a Call on Hold

You can put an active call on hold and then resume the call when you're ready.

Procedure

Step 1 Press **Hold** .

Step 2 To resume a call from hold, press **Hold** again.

Answer a Call Left on Hold for Too Long

When you've left a call on hold too long, you'll be notified with these cues:

- Flashing red line button
- Flashing message indicator on the handset
- Visual notification on the phone screen
- Ringing notification on the phone if a hold reminder is configured with phone web page

Procedure

Press **Hold**  or **Resume** to resume the held call.

Swap Between Active and Held Calls

You can easily switch between active and held calls.

Procedure

Press the line button for the held call, then press **Resume** to resume that call and place the other call on hold automatically.

Call Park

You can use your phone to park a call. You can then retrieve the call either from your phone or another phone, such as a phone at a coworker's desk or in a conference room.

A parked call is monitored by your network so you won't forget about it. If the call remains parked for too long, you hear an alert. You can then answer, decline to answer, or ignore the call on your original phone. You can also continue retrieving it from another phone.

If you don't answer the call within a certain length of time, it's routed to voicemail or another destination, as set by your administrator.

Place a Call on Hold with Call Park

You can park an active call that you answered on your phone and then use another phone in the call control system to retrieve the call.

You can also park a call on your own phone. If so then you may not hear a recording.

You can park only one call at the call park number.

Before You Begin

Your call must be active.

Procedure

-
- Step 1** Press **Park**.
Your phone plays a recorded message that asks for the number of the parked call.
 - Step 2** (Optional) If you have call park configured on a key expansion module, press the call park line key.
 - Step 3** Enter the number and press **Pound (#)**.
 - Step 4** (Optional) Communicate the parked number to the person retrieving the call.
-

Retrieve a Call on Hold with Call Park

You can pick up a parked call from anywhere in your network.

Before You Begin

You need the number that was used to park the call.

Procedure


- Step 1** Press **Unpark**.
- Step 2** (Optional) Press the line key that has busy lamp field with call pickup configured to retrieve a call on hold.
- Step 3** Enter the number where the call is parked followed by **Pound (#)**.
You can also enter **Pound (#)** to retrieve the parked call. If you retrieve a call parked on your own phone, you may not need to enter a number.
-

Forward Calls

You can forward calls from any line on your phone to another number. Call forward is phone-line specific. If a call reaches you on a line where call forwarding is not enabled, the call rings as usual.

There are two ways of forwarding your calls:

- Forward all calls
- Forward calls in special situations, such as when the phone is busy or there is no answer.

Verify that your calls are forwarded by looking for the **Fwd All**  icon in the line label.

Procedure

- Step 1** Press **Forward** on any idle line from which you want to forward your calls.
- Step 2** Enter the call forward target number exactly as you would dial it from your phone, or select an entry from your list of recent calls.
- Step 3** Press **Call** to forward all calls to the specified number.
-

Related Topics

[Forward Call in Specific Situations with the Phone Web Page, on page 36](#)
[Phone Web Page, on page 7](#)

Forward Call in Specific Situations with the Phone Web Page

Use the phone web page to set up your phone to forward all calls during specific situations, such as when your phone is busy.

You can also set up call forward from your user preferences.

Procedure

- Step 1** On the phone web page, click **User Login > Voice > User**.
- Step 2** Under **Call Forward** section, set the **Cfwd Settings** to **Yes** and enter a phone number for each of the call forwarding services that you want to enable:

- **Cfwd All Dest**—Forwards all calls.
- **Cfwd Busy Dest**—Forwards calls only if the line is busy.
- **Cfwd No Ans Dest**—Forwards calls only if the line is not answered.
- **Cfwd No Ans Delay**—Assigns a response delay time.

If your administrator disables the feature key synchronization (FKS) on your phone, you can enter the value as number of seconds after which call needs to be forwarded.

If your administrator enables feature key synchronization (FKS) on your phone, you can enter the value as number of rings after which call needs to be forwarded.

- Step 3** Click **Submit All Changes**.
-

Related Topics

[Phone Web Page Preferences](#), on page 66

[Phone Web Page](#), on page 7

Transfer Calls


You can transfer an active call to another person.

Transfer a Call to Another Person

When you transfer a call, you can stay on the original call until the other person answers. This gives you an opportunity to talk privately with the other person before you remove yourself from the call. If you don't want to talk, then transfer the call before for the other person answers.

You can also swap between both callers to consult with them individually before you remove yourself from the call.

Procedure

- Step 1** From a call that is not on hold, press **Transfer** .
 - Step 2** Enter the other person's phone number.
 - Step 3** (Optional) Wait until you hear the line ring or until the other person answers the call.
 - Step 4** (Optional) Press the line key to return to the held call.
 - Step 5** Press **Transfer** again.
-


Consult Before You Complete a Transfer

Before you transfer a call, you can talk to the person that you're transferring the call to.

Before You Begin

You have an active call that needs to be transferred.

Procedure


- Step 1** Press **Transfer** .
 - Step 2** Enter the phone number for the party you want to transfer.
 - Step 3** When the other person answers, you can talk to them.
 - Step 4** (Optional) Press the line key to return to the held call.
 - Step 5** (Optional) Press the line key to return to the transfer target phone number.
 - Step 6** Press **Transfer** to complete the transfer.
-

Conference Calls and Meetings


You can talk with several people in a single call. You can dial another person and add them to the call. If you have multiple phone lines, you can join two calls across two lines. The conference ends when all participants hang up.

Add Another Person to a Call

Procedure

- Step 1** From an active call, press **Conference** .
 - Step 2** Enter the phone number for the party you want to add and press **Dial**.
 - Step 3** Press **Conference**.
The conference begins.
-


Conference with a Star Code

Press the **Conference**  button only once to combine many active calls into a conference and talk to several people in a single call.

Before You Begin

Your administrator has added a star code to the **Conference**  button from the phone web page.

Procedure

- Step 1** Make a call from a line and wait for an answer.
 - Step 2** Use the same line to call another number and wait for an answer. You can use the same line to call other numbers.
 - Step 3** Press **Conference**  only once.
All numbers are added to the conference call and you see the star code that represents the conference bridge URL with one of the active call.
-

Page a Group of Phones (Multicast Paging)

Your administrator can configure your phone as a part of a paging group. In a paging group, your phone can automatically answer pages from other Multiplatform phones in the phone system. Each paging group has a unique number associated with it. Your administrator gives you the configured paging group numbers. When your phone is paged, you hear three short beeps. The phone establishes one-way audio between you and the phone that called you. You do not have to accept the page.

Procedure

Dial the number of the paging group.

Multiple Lines

If you share phone numbers with other people, you could have multiple lines on your phone. When you have multiple lines, you have more calling features available to you.

Answer the Oldest Call First

You can answer the oldest call available on all your phone lines, including Hold Reversion and Park Reversion calls that are in an alerting state. Incoming calls always have priority over Held or Park Reversion calls.

When working with multiple lines, you typically press the line button for the incoming call you want to answer. If you just want to answer the oldest call regardless of line, press **Answer**.

View All Calls on Your Phone

You can view a list of all your active calls—from all your phone lines—sorted in chronological order, oldest to newest.

The list of all calls is useful if you have multiple lines or if you share lines with other users. The list displays all your calls together.

Shared Lines

You can share a single phone number with one or more of your coworkers. For example, as an administrative assistant, you might be responsible for screening calls for the person that you support.

When you share a phone number, you can use that phone line just like you would any other line, but you should be aware of these special characteristics about shared lines:

- The shared phone number appears on all phones that share the number.
- If your coworker answers the call, the shared line button and the session button are solid red on your phone.
- If you put a call on hold, your line button is solid red and the session button pulses red. Your coworker's line button is also solid red and the session button pulses red.

Add Yourself to a Call on a Shared Line

You or your coworker can join a call on the shared line. Your administrator needs to enable the feature on your phone.

If a user with whom you share a line has privacy turned on, you can't see their line settings and you can't add yourself to their call.

Procedure



-
- Step 1** Press the line button for the shared line.
Step 2 Press **Barge** or **BargeSilent**.
-

Record a Call

When you are on an active call, you can record it. You might hear a notification tone as you record the call.

During a recording, you see different icons in different recording state. You see the icons on the Calls screen and also on the line key on which you are recording a call.

Table 6: Recording Icons

| Icon | Meaning |
|---|------------------------|
|  | Recording in progress. |
|  | Recording paused |

Before You Begin

Your administrator enables your phone with call recording.

Procedure

-
- Step 1** Press **Record** while on an active call.
Step 2 (Optional) While recording is in progress, you can press **PauseRec** to pause the recording.
Step 3 (Optional) Press **ResumeRec** to resume the recording
Step 4 (Optional) Press **StopRec** to stop the recording.
Step 5 Press **End Call** to end the call.
-

Call Center Features

Your administrator configures your phone as a call center phone.

Sign In as a Call Center Agent

When you are ready to start your work as a call center agent, you need to sign into the phone and set your status.

Procedure

- Step 1** Press **AgtSgnIn**.
 - Step 2** Press **Agt status**.
 - Step 3** Highlight the **Available** status.
 - Step 4** Press **Select**.
-

Sign Out as a Call Center Agent

When you are ready to end your work as a call center agent, you change your status and sign out of the phone. After you sign out, you do not receive more call center calls.

If you are on a call and know that you will sign off as soon as the call completes, you can change your status to **Wrap-up**.

Procedure

Press **AgtSgnOut**.

Change Your Status as a Call Center Agent

From time to time, you may need to take a brief break. To do that, you change your status so that calls will not ring on your phone.

Procedure

- Step 1** Press **Agt status**.
 - Step 2** Highlight the **Unavailable** status.
 - Step 3** Press **Select**.
 - Step 4** When you are available again, press **Agt status**.
 - Step 5** Highlight the **Available** status.
 - Step 6** Press **Select**.
 - Step 7** Highlight the **Wrap-up** status.
 - Step 8** Press **Select**.
-

Accept a Call Center Call

When you sign into the phone as a call center agent and your phone status is set to available, your phone are ready to accept call center calls. Before you answer a call, you see information about the call.

Procedure

- Step 1** When you receive a call, you will see the call information page, press **Back** to exit and then press **Answer** to accept it.
 - Step 2** Press **Call Info** to see the call details.
 - Step 3** At the end of the call, press **End call**.
-

Hold an Agent Call

When you are on a call center call, you can put the caller on hold and return to the call. While the call is held for a long time, you will hear a reminder tone and a ring splash on the phone screen.

Procedure

- Step 1** Press **Hold**.
 - Step 2** When you are ready to return, select the held call and press **Resume**.
-

Set a Disposition Code While on a Call Center Call

During an active call or when your status is set to wrap-up state after a call, you can assign a disposition code to a customer call. Disposition code are quick labels that you apply to call records to describe a call. It is a easy way to label calls and keep track of customer contact history so that no detail about the call are missed.

Before You Begin

Your administrator enables your phone to add a disposition code.

Procedure

- Step 1** Press **Disp Code**.
 - Step 2** Press **Ok**.
-

Trace a Call

You can trace an active call and the last incoming call in any agent status.

Before You Begin

Your administrator enables your phone to trace a call.

Procedure

From an active call or after a call, press **Trace**.

Escalate a Call to a Supervisor

When you need to escalate a call, you can add your supervisor to a conference call with you and your caller.

Before You Begin

Your administrator enables emergency escalation on your phone.

Procedure

-
- Step 1** From an active call, press **Emergency**.
- Step 2** In the **Emergency Escalation** window, click **OK**.
You can enter preferred emergency escalation number, or you can leave it empty if you do not have any supervisor preference. You will not see any emergency escalation number.
-



Contacts

- [Corporate Directory, page 45](#)
- [Broadsoft Directory, page 46](#)
- [LDAP Directory, page 47](#)
- [Instant Message and Presence Contacts, page 47](#)
- [Personal Address Book, page 49](#)


Corporate Directory

You can look up a coworker's number from your phone, which makes it easier to give them a call. Your administrator sets up and maintains the directory.

Your phone supports three types of corporate directories—Lightweight Directory Access Protocol (LDAP) Directory, Broadsoft Directory, and a Cisco XML Directory.

Dial a Contact in the Corporate Directory

Procedure

- Step 1** Press **Contacts** .
 - Step 2** Select **Corporate Directory**.
 - Step 3** Select a search criteria.
 - Step 4** Enter your search criteria and press **Submit**.
 - Step 5** Select the contact and press **Dial**.
-

Broadsoft Directory


You can search and view your personal, group, and enterprise contacts in your Broadsoft Directory, which makes it easier to give them a call. Your administrator configures the Broadsoft Directory in your phone. This application feature uses BroadSoft's Extended Services Interface (XSI).

Search for a Contact in Your Broadsoft Directory (Simple Search)

Before You Begin

- Your administrator enables the Broadsoft Directory in your phone.
- You or your administrator sets up your Broadsoft Directory user group type as **Enterprise**, **Group**, or **Personal**.

Procedure


- Step 1** Press **Contacts** .
 - Step 2** Select **Broadsoft Directory**.
You may see the name as the directory name that you have configured for your Broadsoft Directory.
 - Step 3** Select **Simple Search**.
 - Step 4** Enter your search criteria, and press **Submit**.
-

Search for a Contact in Your BroadSoft Directory (Advance Search)

Before You Begin

Set up your Broadsoft Directory user group type as Enterprise or Group.

Procedure


- Step 1** Press **Contacts** .
 - Step 2** Select **BroadSoft Directory**.
 - Step 3** Select **Advance Search**.
 - Step 4** Select a search criteria.
You can search a contact in the BroadSoft directory by Last Name, First Name, User ID, Number, Extension, Department, and Email.
 - Step 5** Enter your search criteria, and press **Submit**.
-

LDAP Directory

The Cisco IP Phone supports Lightweight Directory Access Protocol (LDAP) v3. You can search for a specified LDAP directory for a name, phone number, or both. LDAP-based directories, such as Microsoft Active Directory 2003 and OpenLDAP-based databases, are supported.

Search for a Contact in Your LDAP Directory

Procedure

- Step 1** Press **Contacts** .
 - Step 2** Select **LDAP Directory**.
 - Step 3** Enter your search criteria.
You can search by first name and last name of a contact.
 - Step 4** Press **Submit**.
-

Instant Message and Presence Contacts

Instant message and presence (IM&P) contacts display their presence information. You can see if the person is available, busy, or unavailable, or if the person does not want to be disturbed.

You use the UC-One Communicator to manage your lists of contacts. Your phone gets your lists of contacts from the UC-One Communicator server.

When you use the phone, the phone sends status information to the UC-One Communicator.

Presence

Your company may use the “UC-One Communicator” service and integrate it with the phone. You can use this service to display the status of your contacts.


On the phone, your status is displayed on the status line of the phone. You will see one of these options: Available, Away, Do not disturb, Offline.

For more information on the “UC-One Communicator” service, see the Broadsoft documentation.

Make a Call to an IM and Presence Contact

When you call someone on your IM&P contacts, their presence state is displayed in your call history.


Procedure

- Step 1** Press **Contacts** .
- Step 2** Select **IM&P**.
- Step 3** Select a directory.
- Step 4** Select an entry.
The entry shows the status of your contact.
- Step 5** (Optional) Press **Detail** to view the contact details and press **Back** to return to the contacts list.
- Step 6** Press **Call**.
-

Change Your Presence State

Because the phone is always available, you need to set your presence manually on the phone.


Procedure

- Step 1** Press **Contacts** .
- Step 2** Press **Presence**.
- Step 3** Select your presence from the list.
- Available—You can take a call.
 - Away—You have stepped away from the phone for a short time.
 - Do not disturb—You don't want to take a call.
 - Offline—You are not available to take calls. Typically, you use this presence when you leave the phone for long periods of time.
-

Personal Address Book

Add a New Contact to Your Personal Address Book

Procedure

- Step 1** Press **Contacts** .
 - Step 2** Select **Personal Address Book**.
 - Step 3** Press **Add** or you can press the **Select** button.
 - Step 4** Enter a name and at least one phone number.
 - Step 5** Select a custom ringtone for the contact.
 - Step 6** Press **Save** to add the entry to your personal directory.
-


Add a New Contact to Your Personal Address Book with Phone Web Page

Procedure

- Step 1** On the phone web page, select **User Login > Personal Directory**.
 - Step 2** Click **Add to Personal Directory**.
 - Step 3** Add name, work number, mobile number, and home number.
 - Step 4** Click **Submit All Changes**.
-


Search for a Contact in Your Personal Address Book

Procedure

- Step 1** Press **Contacts** .
 - Step 2** Select **Personal Address Book**.
 - Step 3** Select **Option > Search**.
 - Step 4** Enter the address entry to search for, and press **Submit**.
You can only search by name (case insensitive). Search by number is not supported.
-


Call a Contact in Your Personal Address Book

Procedure

- Step 1** Press **Contacts** .
 - Step 2** Select **Personal Address Book** and search for an entry.
 - Step 3** Select the personal address book entry that you want to dial.
 - Step 4** Press **Call**.
-


Edit a Contact in Your Personal Address Book

Procedure

- Step 1** Press **Contacts** .
 - Step 2** Select **Personal Address Book** and search for an entry.
 - Step 3** Select the entry you want to change.
 - Step 4** Press **Edit**.
 - Step 5** Modify the entry information.
 - Step 6** Press **Save** to modify a phone number.
-

Remove a Contact from Your Personal Address Book

Procedure

- Step 1** Press **Contacts** .
 - Step 2** Select **Personal Address Book**.
 - Step 3** Select **Search address entry**.
 - Step 4** Select the address entry and press **Option > Delete** to delete the entry.
-



Recent Calls

- [Recent Calls List, page 51](#)
- [View Your Recent Calls, page 51](#)
- [Return a Recent Call, page 52](#)
- [Clear the Recent Calls List, page 53](#)
- [Create a Contact From a Recents Record, page 53](#)
- [Delete a Call Record, page 53](#)
- [Delete All Call Records, page 54](#)

Recent Calls List

Use the Recents list to see the 180 most recent individual calls and call groups.

If your Recents list reaches the maximum size, the next new entry overwrites the oldest entry in the list.

View Your Recent Calls


Check to see who's called you recently.

**Note**

Each line has missed call badging. You can view the number of missed calls per line on the phone screen. The maximum missed call badge is 99. When you view either the All calls or Missed calls list on the phone screen for a particular line, the missed call badge for the selected line gets cleared.

The missed call badge and the actual number of missed calls may be different due to a display limit of 180 calls on the Recents list. This limit consists of outgoing calls, missed calls, and incoming calls. Also, there can be some old missed calls that get added to the count for the missed call badge. This can get overwritten in the Recents list.

Procedure


- Step 1** Select a line to view.
- Step 2** Press **Applications** .
- Step 3** Select **Recents**.
- Step 4** Choose to view all recent calls, or to view a certain kind of recent call.
- All Calls
 - Missed Calls
 - Received Calls
 - Placed Calls
 - Server All calls

If you choose **Server All calls**, you can view call logs stored on and transferred from the server. To enable this, your administrator configures your phone with BroadSoft's Extended Services Interface (XSI) call log ability.

- Step 5** Press **Select**.
-


Return a Recent Call

Procedure

- Step 1** Press **Applications** .
- Step 2** Select **Recents**.
- Step 3** Select the call record that you want to dial.
- Step 4** (Optional) Press **Edit call** to edit the call record.
- Step 5** Press **Call**.
-

Clear the Recent Calls List

Procedure

- Step 1** Select a line to view.
- Step 2** Press **Applications** .
- Step 3** Select **Recents**.
- Step 4** Choose to view all recent calls, or to view a certain kind of recent call.
- All Calls
 - Missed Calls
 - Received Calls
 - Placed Calls
- Step 5** Press **Select**.
- Step 6** Press **Delete list**.
- Step 7** Press **Delete**.
-


Create a Contact From a Recents Record

Procedure

- Step 1** Display a Recents record.
- Step 2** Press **Options**.
- Step 3** Press **Add to address book**.
-

Delete a Call Record

Procedure

- Step 1** Press **Applications** .
- Step 2** Select **Recents**.
- Step 3** Choose to view all recent calls, or to view a certain kind of recent call.


- All Calls
- Missed Calls
- Received Calls
- Placed Calls

- Step 4** Press **Select**.
- Step 5** Highlight the individual record or call group that you want to delete.
- Step 6** Press **Delete entry**.
- Step 7** Press **Delete** again to confirm.
- Step 8** Press **Back** .
-

Delete All Call Records

You can delete all call history records on your phone.

Procedure

- Step 1** Press **Applications** .
- Step 2** Select **Recents**.
- Step 3** Press **Recents**.
- Step 4** Select **Option > delete All**.
- Step 5** Press **Delete** again to confirm.
-




Voicemail

- [Your Voicemail Account, page 55](#)
- [Check for New Voice Messages, page 56](#)
- [Access Voicemail, page 56](#)
- [Access Audio Voicemail, page 56](#)

Your Voicemail Account

You can access your voice messages directly from your phone. But your administrator must set up your voicemail account, and may also set up your phone to access the voicemail system.

The **Messages**  button on your phone acts as a speed dial into the voicemail system.


When you aren't at your desk, you can call your voicemail system to access your voicemail. Your administrator can give you the voicemail system phone number.

Because each voicemail system is different, we can't tell you how to use your voicemail system. For information about your voicemail commands, see the voicemail system user documentation or contact your administrator.

Set Up Voicemail on Your Phone

If your administrator has not set up your voicemail phone number on your phone, you can set it up yourself.

Procedure

- Step 1** Press **Applications** .
 - Step 2** Select **User preferences > Call preferences**.
 - Step 3** Enter your voicemail phone number in **Voice mail**.
 - Step 4** Press **Set**.
-

Check for New Voice Messages


To find out if you have new voicemail messages, look for one of these signs:

- The light strip on your handset is solid red.
- The number of missed calls and voicemail messages is displayed on your screen. If you have more than 99 new messages, a plus (+) sign is displayed.
- An exclamation mark (!) indicates urgent voicemail messages.

You will also hear a stutter tone played from your handset, headset, or speakerphone when you use a phone line. This stutter tone is line-specific. You only hear it when you use a line that has voice messages.

Access Voicemail

Procedure

- Step 1** Press **Messages** .
- Step 2** Follow the voice prompts.
-

Access Audio Voicemail

Depending upon how your administrator has set up your phone, you can retrieve your voicemail without viewing a list of messages. This option is useful if you prefer a list of voicemail messages, but you occasionally access your messages without the visual prompts.

Procedure

- Step 1** In the screen, press the **Audio** softkey.
- Step 2** When prompted, enter your voicemail credentials.
-




Settings

- [Settings Overview](#), page 57
- [User Preferences Menu](#), page 57
- [Device Administration Settings](#), page 64
- [Phone Web Page Preferences](#), page 66
- [Restart Your Phone](#), page 69

Settings Overview

You can customize your phone in a number of ways:

- From the menus on the phone, accessed from the **Applications**  button. The common settings menus are:
 - User preferences
 - Device administration
- From the phone web page.

User Preferences Menu

You can customize many settings for your phone from the **User preferences** menu. The menu groups settings according to functions.

Call Preferences

The **User preferences > Call preferences** menu allows you to set the way your phone handles calls.


Forward Calls in Specific Situations from Your Phone

You can set up your phone so that calls are forwarded during specific situations, such as when your phone is busy.

Before You Begin



Call forwarding must be enabled on your phone before you can forward your calls in specific situations.

Procedure

- Step 1** Press **Applications** .
- Step 2** Select **User Preferences > Call Preferences**.
- Step 3** Select **On** to enable call forwarding.
- Step 4** Enter a phone number for each of the call forwarding services that you want to enable:
- **Forward all number**—Forwards all incoming calls to a target phone number.
 - **Forward busy number**—Forwards all incoming calls to a target phone number when the primary line is active.
 - **Fwd no answer number**—Forwards an incoming call that is not answered.
 - **Fwd no answer delay**—Assigns a response delay time.
If your administrator disables the feature key synchronization (FKS) on your phone, you can enter the value as number of seconds after which call needs to be forwarded.
If your administrator enables feature key synchronization (FKS) on your phone, you can enter the value as number of rings after which call needs to be forwarded.
- Step 5** Press **Set**.
-

Set Up Voicemail


Procedure

- Step 1** Press **Applications** .
- Step 2** Select **User preferences > Call preferences > Voice mail**.
- Step 3** Enter a phone number to check voicemail.
If you press the **Messages**  button, it dials the voicemail number and displays the voice message list.
- Step 4** Press **Set** to confirm the assigned number.
-

Block Your Caller ID Display

You can hide your caller name and number from the person whom you are calling.


Procedure

- Step 1** Press **Applications** .
 - Step 2** Select **User preferences > Call preference > Block caller ID**.
 - Step 3** Press **On** you want to block caller ID display, or press **Off** to allow caller ID display.
 - Step 4** Select **Set** to apply the changes.
-

Block an Anonymous Call

You can block an incoming call that does not have caller information.


Procedure

- Step 1** Press **Applications** .
 - Step 2** Select **User preferences > Call Preference > Block anonymous call**.
 - Step 3** Select **On** if you want to block the call that does not have caller information, or select **Off** to allow the call.
 - Step 4** Select **Set** to save the setting.
-

Turn On Do Not Disturb For a Specific Line

Set do not disturb (DND) to silence your phone and suppress incoming call notifications when you need to avoid distractions. You can suppress all incoming call notifications or you can suppress a specific caller notification.


Procedure

- Step 1** Press **Applications** .
 - Step 2** Select **User preferences > Call preferences > Do not disturb**.
 - Step 3** Select a specific line from the list.
 - Step 4** Press **On** to turn on DND or press **Off** to turn off DND.
-

Control the Call Waiting Tone

When you are talking with someone and get another call, you can set the phone to give a call waiting tone.



Procedure

- Step 1** Press **Applications** .
 - Step 2** Select **User preferences > Call preferences > Call waiting**.
 - Step 3** Press **On** you want the call waiting tone, or press **Off** if you don't want the call waiting tone.
 - Step 4** Select **Set** to apply the changes.
-

Secure a Call


You can encrypt calls to protect them from eavesdroppers. You can set up the secure call feature on all outbound calls or for a specific call.

Procedure

- Step 1** Press **Applications** .
 - Step 2** Select **User Preferences > Call Preference > Secure Call**.
 - Step 3** Press **On** to enable secure call feature or press **Off** to disable the secure call feature.
 - Step 4** Press  to save the change and to return to the Call Preferences screen.
-


Set Up an Auto Answer Page

Procedure

- Step 1** Press **Applications** .
 - Step 2** Select **User preferences > Call preference > Auto answer page**.
 - Step 3** Press **On** to enable the Auto answer page or press **Off** to disable Auto answer page.
 - Step 4** Press **Set** to save the changes.
-

Enable the Missed Call Shortcut

Procedure

- Step 1** Press **Applications** .
 - Step 2** Select **User preferences > Call preferences > Missed call shortcut**.
 - Step 3** Press **On** if you want to the shortcut, or press **Off** if you don't want the shortcut.
 - Step 4** Select **Set** to apply the changes.
-


Audio Preferences

The **User preferences > Audio preferences** menu allows you to customize ringtones and how you prefer to answer calls.

Set Your Preferred Audio Device


You can set how you want to answer the call: headset, speaker, or handset.

Procedure

- Step 1** Press **Applications** .
 - Step 2** Select **User preferences > Audio preferences > Preferred audio device**.
 - Step 3** Press **Select** to scroll through the list of devices.
 - Step 4** Press **Set** to save the selection.
 - Step 5** Press **Back** to exit.
-

Change the Ringtone

Procedure

- Step 1** Press **Applications** .
 - Step 2** Select **User preferences > Audio preferences > Ext (n) - Ring tone**, where n= extension number.
 - Step 3** Scroll through the list of ringtones and press **Play** to hear a sample.
 - Step 4** Press **Select** softkey and then **Set** softkey to save a selection.
 - Step 5** Press **Back** to exit.
-


Screen Preferences

The **User preferences > Screen preferences** menu allows you to set your phone screen display options.

Change the Screen Saver

You can enable your phone screen saver, and specify its appearance and the amount of time for the phone to be idle before the screen saver appears.


Procedure

- Step 1** Press **Applications** .
- Step 2** Select **User preferences > Screen preferences > Screen saver**.
- Step 3** Select **On** to enable the screen saver, or press **Off** to turn the screen saver off.
- Step 4** Select **Screen saver settings** to choose the settings:
- **Screen saver type**—Choose one of the following options:
 - **Clock**—Displays a rounded clock with the wallpaper in the background.
 - **Download Picture**—Displays a picture pushed from the phone web page.
 - **Logo**: Displays a logo as the phone screensaver. This image is added in the Logo URL field of the phone web page.
 - **Lock**—Displays a lock icon on the phone screen.
 - **Trigger interval**—Enter the number of seconds that the phone remains idle before the screen saver turns on.
 - **Refresh interval**—Enter the number of seconds before the screen saver should refresh (if, for example, you chose a rotation of pictures).
- Step 5** Press **Set**.
-

Set the Backlight Timer


You can adjust the length of time that the phone screen is bright before it automatically dims.

Procedure

- Step 1** Press **Applications** .
- Step 2** Select **User preferences > Screen preferences > Backlight timer**.
- Step 3** Press **Select** to scroll through the list and select a duration for which the backlight remains on:
- 10 seconds
 - 20 seconds
 - 30 seconds
 - Always On
 - Off
- Step 4** Press **Set** to apply the selection.
-

Adjust the Phone Screen Contrast


Procedure

- Step 1** Press **Applications** .
- Step 2** Select **User preferences > Screen preferences > Contrast level**.
- Step 3** Press the Navigation cluster up or down to increase or decrease the brightness.
- Step 4** Press **Save**.
-

Set the Phone Wallpaper

You can select the wallpaper (background) for the phone screen.

Procedure


- Step 1** Press **Applications** .
- Step 2** Select **User preferences > Screen preferences > Wallpaper**.
- Step 3** Press **Select** to scroll through the list and select a wallpaper.
- Step 4** Press **Set** to apply the selection.
-

Attendant Console Preferences

The **User preferences > Attendant console preferences** menu allows you to customize how calls display.

Change the Display Mode

Procedure

- Step 1** Press **Applications** .
- Step 2** Select **User preferences > Attendant console preferences > Display mode**.
The following options are available:
- **Name**
 - **Ext**
 - **Both**
- Step 3** Choose the display mode and press **Set**.
-


Device Administration Settings

You can set some other preferences from the phone in the **Device administration** menu.

Change the Time Format

You can change the current time format that the phone screen displays.

Procedure

- Step 1** Press **Applications** .
- Step 2** Select **Device administration > Date/Time > Time format**.
To set daylight savings, select **Device administration > Date/Time > Daylight Savings**. Press **On** to turn on the daylight savings and press **Off** to turn it off.
- Step 3** (Optional) Select **Device administration > Date/Time > Time Zone**.
- Step 4** Select a time format and press **Set** to apply the changes.
-

Change the Date Format

You can change the date format that you want to see on your phone screen.


Procedure

- Step 1** Press **Applications** .
 - Step 2** Select **Device administration** > **Date/Time** > **Date format**.
 - Step 3** Select a date format and press **Set** to apply the changes.
-

Set Language

Depending upon how your phone is configured, you may be able to change the language used by your phone.

Procedure


- Step 1** Press **Applications** .
 - Step 2** Select **Device administration** > **Language**.
 - Step 3** Select a language from the list of available languages.
 - Step 4** Select **Save**.
-

Set up Power Save

You can put your phone into power save mode when your phone is idle. If your phone is not idle, you can't turn power save on and you see a message on the screen.

When your phone is in power save mode, the screen is not lit and the **Select** button is lit. You press the **Select** button to wake up the phone.

Procedure

- Step 1** Press **Applications** .
 - Step 2** Select **Device administration** > **Power save**.
 - Step 3** Select **OK**.
-


Set Password

Reset your phone password regularly to maintain network security. Keep all passwords in a safe place to avoid theft.

Before You Begin

You must have your existing password.

Procedure

- Step 1** Press **Applications** .
- Step 2** Select **Device administration** > **Set password**.
- Step 3** Enter your current password in the Old password field.
- Step 4** Enter your new password in the New password and the Reenter new password fields.
- Step 5** Select **Save**.
-

Phone Web Page Preferences

You can customize some settings from the phone web pages.

Related Topics

[Phone Web Page, on page 7](#)

[Forward Call in Specific Situations with the Phone Web Page, on page 36](#)

Assign a Ring Tone to an Extension with the Phone Web Page

Procedure

- Step 1** On the phone web page, select **User Login** > **Voice** > **Ext(n)**, where **(n)** is the number of an extension.
- Step 2** Under **Call Feature Settings**, use the **Default Ring (n)** drop-down list box to specify one of the following:
- No Ring
 - 1 through 9—Choose one of the available ring tones.
- Step 3** Click **Submit All Changes**.
-

Turn on DND on for All Lines from the Phone Web Page

Procedure

-
- Step 1** On the phone web page, select **User Login > Voice > User**.
- Step 2** Under **Supplementary Services**, set **DND Settings** to **Yes**.
You can turn on DND on for all lines if your administrator hasn't enabled feature key sync (FKS).
- Step 3** Click **Submit All Changes**.
-

Configure the Screen Saver with the Phone Web Page

You can configure a screen saver for the phone. When the phone is idle for a specified time, it enters screen saver mode.

Any button press returns the phone to normal mode. If a user password is set, the user must enter it to exit screen saver mode.

Procedure

-
- Step 1** On the phone web page, select **User Login > Voice > User**.
- Step 2** In the **Screen** section, set up the fields as described in the below table.

| Parameter | Description |
|---------------------|--|
| Screen Saver Enable | Select Yes to enable a screen saver on the phone. When the phone is idle for a specified time, it enters screen saver mode. Default: No |
| Screen Saver Type | Types of screen saver. Options you can choose: <ul style="list-style-type: none"> • Clock—Displays a digital clock on a plain background. • Download Picture—Displays a picture pushed from the phone webpage. • Logo: Displays a logo on the phone screen. Add a logo image in the Logo URL field. • Lock —Enables locking of the screensaver. |
| Screen Saver Wait | Amount of idle time before screen saver displays. Enter the number of seconds of idle time to elapse before the screen saver starts. Default: 300 |

| Parameter | Description |
|----------------------|---|
| Picture Download URL | URL locating the (.png) file to display on the phone screen background. When you enter an incorrect URL to download a new wallpaper, the phone fails to upgrade to the newer wallpaper and displays the existing downloaded wallpaper. If the phone does not have any wallpaper downloaded earlier, it displays a gray screen. |
| Logo URL | Enter a URL or path for the location where the logo image is saved. If you select logo as as screensaver type, this image displays as a screensaver on the phone screen. |

Step 3 Click **Submit All Changes**.

Adjust the Backlight Timer from Phone Web Page

You can save energy by disabling the backlight on each phone at a preset time. The phone's desktop remains visible, even with the backlight off.

Procedure

- Step 1** On the phone web page page, select **User Login > Advanced > Voice > User**.
 - Step 2** Under **Screen**, select a duration for the **Back Light Timer** parameter.
 - Step 3** In the **LCD Contrast** field, enter a number for the desired brightness.
-

Add a Logo as a Phone Background

To add a logo icon as your phone screen background, add it from phone web page.


Procedure

- Step 1** On the phone web page, select **User Login > Voice > User**.
 - Step 2** In the **Screen** section, select **Logo** from the **Phone Background** field and in the **Logo URL** field enter a URL or path for the location where the logo image is saved.
 - Step 3** Click **Submit All Changes**.
After the logo is added in the phone background, if you select **Default** from the **Phone Background** list and save the changes, the logo icon on the phone screen will disappear.
-

Restart Your Phone

You may have to reboot your phone for a software upgrade or other changes to take effect. Your settings or other customizations do not change.

Procedure

- Step 1** Press **Applications** .
- Step 2** Select **Device administration** > **Restart**.
- Step 3** Select **OK** to confirm that you want to reboot your phone.
-



Accessories

- [Supported Accessories, page 71](#)
- [Headsets, page 71](#)

Supported Accessories

The Cisco IP Phone 6800 Series supports both Cisco and third-party accessories.

In the following table, an X indicates support for an accessory by a particular phone model and a dash (-) indicates no support.

Table 7: Accessory Support for the Cisco IP Phone 6800 Series

| Accessory | Type | Cisco IP Phone 6841 | Cisco IP Phone 6851 |
|--------------------------------|-----------------|---------------------|---------------------|
| Third-Party Accessories | | | |
| Headsets | Analog | X | X |
| | Analog Wideband | X | X |
| Microphone | External | - | - |
| Speakers | External | - | - |
| Wall Mount | External | X | X |

Headsets

Check with the headset manufacturer to confirm whether you can use it with your Cisco phone.

If you plug a headset into the phone during an active call, the audio path automatically changes to the headset.

Standard Headsets

You can use a standard headset with your desk phone.

Connect a Standard Headset

Standard headsets plug into the back of the phone.

Procedure


Plug the headset into the headset jack on the back of the phone and press the cable into the cable channel. The headset jack is beside the handset jack.

Enable an E-Hookswitch Headset

Electronic Hookswitch headsets use a base station and a wireless headset. The base station plugs into your phone headset jack. After installing the headset, you enable it on the phone web page.

The Cisco IP Phone 6851 supports Electronic Hookswitch headsets. The Cisco IP Phone 6841 does not support these headsets.

Procedure

-
- Step 1** Press **Applications** .
- Step 2** Select **Settings > E-Hookswitch connected**.
- Step 3** Select **Yes**.
-



Product Safety and Security

- [Safety and Performance Information, page 73](#)
- [Compliance Statements, page 74](#)
- [Cisco Product Security Overview, page 75](#)
- [Important Online Information, page 76](#)

Safety and Performance Information

Power Outage

Your access to emergency service through the phone requires that the phone receive power. If a power interruption occurs, service or emergency calling service dialing does not function until power is restored. If a power failure or disruption occurs, you may need to reset or reconfigure the equipment before you can use service or emergency calling service dialing.

External Devices

We recommend that you use good-quality external devices that are shielded against unwanted radio frequency (RF) and audio frequency (AF) signals. External devices include headsets, cables, and connectors.

Depending on the quality of these devices and their proximity to other devices, such as mobile phones or two-way radios, some audio noise may still occur. In these cases, we recommend that you take one or more of these actions:

- Move the external device away from the source of the RF or AF signals.
- Route the external device cables away from the source of the RF or AF signals.
- Use shielded cables for the external device, or use cables with a better shield and connector.
- Shorten the length of the external device cable.
- Apply ferrites or other such devices on the cables for the external device.


Cisco cannot guarantee the performance of external devices, cables, and connectors.

**Caution**

In European Union countries, use only external speakers, microphones, and headsets that are fully compliant with the EMC Directive [89/336/EC].

Ways to Provide Power to Your Phone

You can provide power to your phone in one of two ways:

- Use the power adapter that comes with your phone.
- If your network supports Power over Ethernet (PoE), you can plug your phone into the network. Plug an Ethernet cable into the Ethernet phone port  and into the network.

If you are not sure whether your network supports PoE, check with your administrator.

Phone Behavior During Times of Network Congestion

Anything that degrades network performance can affect phone voice and video quality, and in some cases, can cause a call to drop. Sources of network degradation can include, but are not limited to, the following activities:

- Administrative tasks, such as an internal port scan or security scan
- Attacks that occur on your network, such as a Denial of Service attack

Compliance Statements

FCC Compliance Statements

The Federal Communications Commission requires compliance statements for the following:

FCC Part 15.21 Statement

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

FCC RF Radiation Exposure Statement

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. End users must follow the specific operating instructions for satisfying RF exposure compliance. This transmitter must be at least 20 cm from the user and must not be collocated or operating in conjunction with any other antenna or transmitter.

FCC Receivers and Class B Digital Statement

This product has been tested and complies with the specifications for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used according to the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which is found by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna
- Increase the separation between the equipment or devices
- Connect the equipment to an outlet other than the receiver's
- Consult a dealer or an experienced radio/TV technician for assistance

Compliance Information for Brazil

Art. 6º - 506

This equipment is a secondary type device, that is, it is not protected against harmful interference, even if the interference is caused by a device of the same type, and it also cannot cause any interference to primary type devices.

For more information, go to this URL: <http://www.anatel.gov.br>

Este equipamento opera em caráter secundário, isto é, não tem direito a proteção contra interferência prejudicial, mesmo de estações do mesmo tipo, e não pode causar interferência a sistemas operando em caráter primário.

Site Anatel: <http://www.anatel.gov.br>

Cisco Product Security Overview

This product contains cryptographic features and is subject to U.S. and local country laws that govern import, export, transfer, and use. Delivery of Cisco cryptographic products does not imply third-party authority to import, export, distribute, or use encryption. Importers, exporters, distributors, and users are responsible for compliance with U.S. and local country laws. By using this product, you agree to comply with applicable laws and regulations. If you are unable to comply with U.S. and local laws, return this product immediately.

Further information regarding U.S. export regulations can be found at <https://www.bis.doc.gov/policiesandregulations/ear/index.htm>.

Important Online Information

End User License Agreement

The End User License Agreement (EULA) is located here: <https://www.cisco.com/go/eula>

Regulatory Compliance and Safety Information

Regulatory Compliance and Safety Information (RCSI) is located here: https://www.cisco.com/c/en/us/td/docs/voice_ip_comm/cuipph/all_models/regulatory_compliance/english/install/guide/iphrcsi3.html