


PT-EB | Noise Cancelling Bluetooth Speakerphone




1. Package include



2. Product introduction

SP300 is a Smart Wireless Conference speakerphone. This product can connect with PC, tablet and smartphone via Wireless or USB cable. And the speakerphone is a 360° omnidirectional microphone with high quality speaker, it can receive voice all round in a long distance. It is small and portable, convenient for both fixed and mobile office.



- ① Power on/off button
- ② Wireless pair mode button
- ③Volume up button
- Microphone mute button
- S Answering/hanging up/Rejecting call button
- **©** Volume down button
- 7logo indicator



® Daisy chain port

9Type C port

Microphone

Wireless Connection Dongle

3. Indicator Status

| Position | Color | Status |
|----------------|-----------------|--------------------------|
| Indicator pipe | green | Calling/volume+/volume- |
| Indicator pipe | white | Battery charge remaining |
| Indicator pipe | Red | Mute |
| Indicator pipe | Orange flashing | Bettor low |
| Logo Indicator | purple | working |
| Logo Indicator | blue | Wireless connected |
| Logo Indicator | Blue flashing | Wireless pairing |
| Logo Indicator | red | charging |

4. How to power on/off

Press power button and hold on 3s, the logo indicator LED will light up and be purple. Press power button and hold on 3s again, the device will power off and all LED will be off.

200

5. How to charge

Please insert USB cable in the micro USB port of SP300. Then connect USB type A interface with PC's USB port or 5V external charger.

When the device is charging, the logo indicator LED will be red, the LED will be off when it is full charged.




^{*}AC adapter need purchase separately if you want.

^{*}only UL certified ITE power supply can be used. The electrical rated output is 5V DC, 1A current is minimum required.

6. How to connect

1. Connect with PC

- Please use USB cable to connect SP300 with target PC;
- The device will start automatically, the power indicator LED will light up and you can use it through the USB mode;
- Please set the Echo Cancelling Speakerphone SPEAKERPHONE SP300 as default output and input audio device.



2. Connect to smartphone/PC with Bluetooth

 Press power button and hold on 3s to power on the device, the logo indicator LED will light up and be purple, then press the Wireless Pair Mode button and hold on 3s, the logo indicator LED will be blue and flashing, SP300 is in the Wireless pair mode, Then open the Bluetooth in your smartphone or PC, search the device SPEAKERPHONE SP300, connect to use.

If you are using PC, please set the Speaker(SPEAKERPHONE SP300 Stereo) as default Device and set the Headset(SPEAKERPHONE SP300 Hand-Free AG Audio) as default Communication Device in Playback, set the Headphone microphone (SPEAKERPHONE SP300 Hand-Free AG Audio) as default Communication Device in Recording, make sure to choose Set as Default Device to other device, Don't choose the same device as the communications device.

• If one device had connected with SP300 before, press Wireless pair mode button and hold on 3s, the logo indicator LED will be blue and flashing, your smartphone/PC will take the initiative to connect back. The logo indicator will keep lighting.



3. Connect to the PC with Wireless dongle

- If you have problem to connect the device with the Bluetooth attached in your PC, please plug Wireless dongle into any USB port of on your host PC and find "Generic Wireless Radio" in device manager under system. If your PC has internal Wireless module, please disable it firstly;
- Press the Wireless Pair mode button and hold on 3s, the logo indicator LED will light up and be purple, then press the Wireless Pair Mode button and hold on 3s, the logo indicator LED will be blue and flashing, SP300 is in the Wireless pair mode, then open the Bluetooth in your PC, search the device SPEAKERPHONE SP300, connect to use;
- If one device has connected with SP300 before, when power on the device, your smartphone/PC will take the initiative to connect back.
 The wireless indicator will keep lighting;



Note:

- *Ensure that all Wireless devices previously connected to the wireless connection dongle are switched off.
- * This dongle is compatible with windows 10 not Windows 7/8.1, Mac and Linux. If you still want to use this product, we strongly recommend that you could use USB mode as above mentioned.
- * This dongle is optional.

4. Connect to 2 smartphones with Wireless and 1 PC with USB at the same time

- Press power button and hold on 3s, he logo indicator LED will light up and be purple, use USB cable to connect SP300 with target PC, then Press Wireless Pair mode button and hold on 3s, the logo indicator LED will be blue and flashing, then SP300 is in the Wireless pair mode, connect up to ² smartp_hones to use.
- Among all connections, 2 Bluetooth and 1 USB, the speaker will sound the audio which is sent to the speaker first.



- 5. Daisy chain mode
- Power on 2 SP300s, then connect two devices with Daisy chain cable.
- connect one of 2 SP300s to your smartphones in wireless mode or connect to your PC in USB mode, Expand the pickup and playback distance to get more conference space.



Note: When you use it in daisy chain mode, your phone or PC only needs to connect to one of two devices.

7. How to operate

| ICON | FUNCTION | OPERATION |
|------|---|---|
| ds | Power on/off | Press and hold(3s) this button until the logo indicator LED will be purple |
| 0 | Display battery level | Tap this button |
| Ž | Mute/unmute | Tap this button |
| + | Turn up the volume | Tap "+" button, you press it twice, the indicator light will increase by one space |
| _ | Turn down the volume | Tap "-" button, you press it twice, the indicator light will reduce by one space |
| | Answer call | Tap this button |
| 3 | End call | Tap this button |
| | Reject call | Press and hold(3s) this button |
| | Connect new Wireless device | Press and hold(3s) this button to connect with a new Wireless device |
| 0 | disconnect with trusted Wireless device | Press and hold(3s) this button to reconnect/disconnect with trusted Wireless device |

8. Product Specification

| SPECIFICATION | SPEAKERPHONE SP300 |
|-----------------------------|---------------------------------|
| 3F LCII ICATION | SFEARENFIIONE SF 300 |
| Microphones | 6pcs,Omni-directional |
| Speaker | 3W, Dynamic, 40mm |
| Wireless range | Up to 10m(30ft), Class2 |
| Wireless version | 5.0, compatible with |
| | 4.2/4.1/4.0/3.0/2.1 |
| Paired devices | Up to 8 trusted devices |
| Talk time | Up to 18H |
| Operating temperature | 5°C to 40°C (41°F to 104°F) |
| Storage temperature | -5°C to 60°C (23°F to 140°F) |
| Wireless audio bandwidth | A2DP, Wide band |
| Connectivity | USB 2.0 and Wireless connection |
| Type C port | Charging and data connection |
| Daisy chain port | Daisy chain mode |
| Dimensions | D 130mm x H 38.2mm |
| Weight | 290g |

Warning

Only could be used in areas below 2000 meters above sea level;

Only applicable to non-tropical climate conditions.

9. Trouble Shooting

| Problem or Phenomenon | Possible Reasons | Treatments |
|-----------------------------|---|---|
| Can't power on | Low battery | Charge through adapter |
| No sound | Host system audio setting doesn't select the right output device; The speaker volume is very low | Selecting the correct output audio source; Turn up the speaker volume. |
| USB doesn't work | Doesn't use the right USB cable | Please use the original USB cable in the package box. |
| Can't be charged | Adapter issue or battery is full | Change a new adapter; Tap the power button to check the battery level |
| Can't connect with Wireless | The Wireless driver of host device doesn't support audio protocol | Update the latest Wireless driver of your host device. |

10.Warranty

All our products come with one full year warranty from the date of purchase (accessories are out of warranty). It will be out of guarantee if damaged due to incorrectly use or force majeure.

THE FUNCTION DESCRIBED IN THIS MANUAL IS BASED ON TESTING MADE BY OUR FACTORY. SPCIFICATION AND DESIGN MAY BE CHANGED WITHOUT FUTURE NOTICE.

11.Customer support

If you have any problem, please feel free to contact us