

LG Aria Digital Systems

30 Button Key Station User Guide (LKD-30D)

MAKE AN INTERNAL CALL: Ext.No. 100-399

SELECT A LINE: 9 (or 0).

TRANSFER A CALL: TRANS Ext.No. Hangup or wait for an answer then hangup.
or press the DSS button Hangup. (DSS=direct station selection.)

CALL PARKING: dial TRANS 601-619 (**RETRIEVE CALL:** dial 601-619)

Note: Most features can be accessed via the menu. Press TRANS/PGM scroll up & down by the volume keys. Make your selection by pressing the relevant digits.

BGM: (Back Ground Music) TRANS 73 (channel 01-12, 00 to cancel) Hold/Save

BGM THRU PA: TRANS 076,077 or 078 for ports 1,2 or 3. Channel no. Hold/Save

CALL BACK: CALLBK (call-back a busy or no answer extension.)

CALL FORWARD: 554 1=fwd all,2=busy,3=no ans,4=busy/no ans,5=off-net,
6= off-net noans,7=off-net line,0=follow me (add # for VMIB)

CANCEL FORWARD: 554 #

CHANGE INTERCOM MODE: TRANS 12 1=Handsfree, 2=Tone ring, 3=Privacy Handsfree SAVE.

CHANGE RING TONE: TRANS 11 1-4 HOLD/SAVE.

CONFERENCE: 1st Party CONF 2nd Party CONF CONF

EXCLUSIVE HOLD: HOLD HOLD

HEADSET MODE: TRANS 750 Save. Cancel: Trans 751 Save. (Ring modes: 76)

NIGHTSWITCH: DND (at Reception)

TIME/DATE: TRANS 041 MMDDYY save HHMM save (at Reception)

PAGEALL: #00 **INTERNAL:** dial #5 **EXTERNAL:** dial #9

PICKUP: ** Direct Pickup: *7 Ext.No.

PROGRAM DSS KEYS: TRANS DSS (flex key) dial code or Ext.no. SAVE

PROGRAM SYSTEM SPEEDS: TRANS/PGM SPEED 2000-4999 Ph.No. save Name save
MON to exit (at Reception)